

# Allegro™ Pro 4 USB 3.2 Gen 2 Type-C® PCIe® Card

4-Port, 2-Controller, 10Gbps USB-C® PCIe Card  
With USB Type-C Charging

## Quick Start Guide

### You Should Have

The following items should be included in your product package:

- One Allegro Pro 4 USB 3.2 Gen 2 Type-C PCIe Card
- Quick Start Guide

The following items may be required for installation:

- Medium Phillips screwdriver

### Mac® Compatibility

- Mac Pro® 3,1<sup>(1)</sup>, 4,1, 5,1, 7,1 (2019), and 14,8 (2023)
- macOS® 10.12.6+<sup>(2)</sup>

### Windows® Compatibility

- Computer with PCIe slots
- Windows 11, 10, 8.1, 7
- Windows Server 2019, 2016, 2012, and 2008 (64-bit editions)

### Linux® Compatibility<sup>(3)</sup>

- Computer with PCIe slots
- Linux Kernel 5.4.0+
- Ubuntu 20.04.1+

### Thunderbolt™ Compatibility

- Supports USB 3 peripherals when installed in a Thunderbolt to PCIe card expansion system (excluding Thunderbolt 1 to PCIe card expansion systems)

1. The maximum Apple-supported OS for the Mac Pro 3,1 is OS X 10.11. Dostdud1 offers patchers to allow installation of newer versions of macOS for the Mac Pro 3,1. The Apple USB 3 driver in these patched newer versions will support the Allegro card.
2. When installed in a 2019 Mac Pro running macOS Big Sur (macOS 11) this card requires version macOS 11.5 or later; macOS 11.1 – 11.2.2 are not compatible.
3. USB devices connected to the Allegro Pro card may not be detected in some Linux computers. Go to <https://www.sonnettech.com/support/kb/kb.php>, navigate to and click the Allegro Pro 4 USB 3.2 Gen 2 Type A PCIe Card link. Click FAQ to expand the category, and then click FAQ ID 1149 to learn how to resolve the issue.

1

### Installation Preparation

Sonnet strongly recommends that you read the section in your computer's user manual that addresses PCIe card installation, prior to installing the Allegro card into your system.



**Support Note:** When handling computer products, you must take care to prevent components from being damaged by static electricity. Before opening your computer or removing parts from their packages, always ground yourself first by touching a metal part of the computer, such as a port access cover, and work in an area free of static electricity; avoid carpeted areas. Handle all electronic components by their edges, and avoid touching connector traces and component pins.

### Card Installation Steps

1. Shut down your computer or Thunderbolt-to-PCIe card expansion chassis, and then open it to access the expansion card area (PCIe slots); refer to the user's manual for specific information.
2. Locate an available PCIe card slot and remove its access cover.
3. Remove the Sonnet card from its packaging, and then install it into the PCI Express slot; make sure the card is firmly seated and secured.
4. Close the computer or Thunderbolt-to-PCIe card expansion chassis.

2

### Driver Information

*For Mac users,* the drivers that enable this Allegro card to work in your computer or Thunderbolt expansion chassis are installed as part of macOS 10.12.6 and later; the Allegro card is ready to use when you power on your computer.

*For Windows users,* the drivers that enable this Allegro card to work in your computer running supported versions of Windows *except* Windows 7 (32- and 64-bit versions) are installed automatically. For Windows 7 users, please go to [www.sonnettech.com/support/kb/kb.php](http://www.sonnettech.com/support/kb/kb.php). Navigate to and click the Allegro Pro 4 USB 3.2 Gen 2 Type-C PCIe Card link, and then click the Driver link. Locate, download, and install the appropriate drivers. For all other users, update Windows to the latest version to ensure full support and performance.

*For Linux users,* the drivers that enable this Allegro card to work in your computer or Thunderbolt expansion chassis are installed as part of Linux Kernel 5.4 and later; the Allegro card is ready to use when you power on your computer.

3

## Known Limitations and Advice

USB technology and peripherals have some limitations. Refer to your peripheral manufacturers' Web sites for more information.

- Most USB 3.2 (formerly 3.1) devices currently come in two varieties, Gen 1, and Gen 2. Gen 1 devices support data transfer speeds up to 5Gbps, while Gen 2 devices (such as this Sonnet adapter card) support data transfer speeds up to 10Gbps.
- The use of USB-C to USB-A cables is supported, but data transfer speeds are limited to the speeds supported by the cable and device.
- Allegro Pro 4 USB 3.2 Gen 2 Type-C PCIe Card does not support Thunderbolt 3 only peripheral devices, even though they use the same connector. If the peripheral device only has the Thunderbolt icon (⚡) next to its port(s), or on the connector of an attached cable, it will not work with the Sonnet card.
- Many peripherals require additional drivers and application software to operate or have full functionality. Software should be included with the device, or available to download from the manufacturer's Web site. Check the peripheral's user's manual for information about necessary software.
- macOS 10.12.6 erroneously reports a 5Gbps connection when connected at 10Gbps. macOS 10.13+ reports connections correctly.
- While your computer is on, always "eject" any memory card from the operating system before removing it from an attached card reader, or disconnecting the reader (with the card inserted in it) from its cable or the Sonnet card. Also, always "eject", "stop", "unplug", or "put away" any drive (hard drive, SSD, etc.) before disconnecting it from its cable or the Sonnet card's USB-C port.

4

## Contacting Customer Service

The Sonnet Web site located at <https://www.sonnettech.com> has the most current support information and technical updates. Before contacting Customer Service, please check our Web site for the latest updates and online support files, and check this Quick Start Guide for helpful information.

Email support requests generally receive the fastest responses, and are usually processed within a 24-hour period during normal business hours, excluding holidays. When you contact Customer Service, have the following information available so the customer service staff can better assist you:

- Product name
- Computer model
- A System Report (macOS), or a Microsoft System Information MSINFO32 (Windows) report (Windows), along with a description of the issue(s) you are encountering with your device

If further assistance is needed, please contact Sonnet Customer Service at:

**E-mail:** [support@sonnettech.com](mailto:support@sonnettech.com)

**Tel:** 1-949-472-2772

(Monday–Friday, 9 a.m.–5 p.m. Pacific, excluding holidays)

### Japan Customers


Contact Sonnet Customer Service Japan at:

**E-mail:** [jp.support@sonnettech.com](mailto:jp.support@sonnettech.com)

6

- Disconnecting drives while they are transferring or receiving data, may result in damage to the file(s) being transferred or cause your system to hang.
- Although many peripherals may draw power directly from the Sonnet card, other devices require an external power source. Remember to use external power supplies when necessary.
- 1-meter or longer Thunderbolt 3 (40Gbps) cables DO NOT support USB 3.0 (3.1 Gen 1 and 3.2 Gen 1) by design, only Thunderbolt 3 & USB 2.0.

- When this card is installed in a 2023 or 2019 Mac Pro, the cables, adapters and thumbdrives you can connect are limited to those with overmolds (the non-metal part of the USB connector) no thicker than 6.5mm. Due to their non-conventional PCIe backplate openings, 2019 and 2023 Mac Pro computers prevent connectors with larger overmolds from fully connecting to the ports on the Sonnet card.



5



**Support Note:** This document was up to date at the time of printing. However, changes to the hardware or software may have occurred since then. Please check the Sonnet Web site for the latest documentation.

1. Go to <https://www.sonnettech.com/support/kb/kb.php>
2. Navigate to and click the Allegro Pro 4 USB 3.2 Gen 2 Type-C PCIe Card link.
3. Click the Manual link.
4. Click the Allegro Pro 4 USB 3.2 Gen 2 Type-C PCIe Card Quick Start Guide [English] link and then check the Document Version information. If the version listed is later than this document (**revision G**), click the Download Now button for the latest version.



©2024 Sonnet Technologies, Inc. All rights reserved. Sonnet, SONNETTECH, the Sonnettech logotype, and the S logotype are registered trademarks of Sonnet Technologies, Inc. Inc. Mac, the Mac logo, Mac Pro, and macOS are trademarks of Apple Inc., registered in the United States and other countries. Thunderbolt and the Thunderbolt logo are trademarks of Intel Corporation in the U.S. and/or other countries. Other product names are trademarks of their respective owners. Product specifications subject to change without notice. QS-USB3C-4PM-E-E-G-091124